

SER-9582

Plus Radio Service Kit (2 x Alkaline C Batteries)

Warnings

- This kit is for use with Tinytag radio data loggers only.
- Ensure you are using the correct service kit and battery type for your unit.
- Do not short circuit batteries. Do not dispose of batteries in fire. Do not attempt to recharge non-rechargeable batteries. Observe all warnings on the batteries supplied.

Instructions

For use with radio receiver and logger models:

ACSRF-3030-XK, ACSR-4XXX-XK, TGRF-3XXX-XK, TGRF-4XXX-XK

1. Turn off the unit by pressing & holding the on-off switch until the unit's LED lights red.
2. Open the case by undoing the four bolts, starting on opposite diagonals.
3. Remove the old batteries from the unit.
4. Observing the correct polarity, and ensuring that the battery contacts are clean, fit the two new batteries.

 **Batteries must be replaced in pairs, do not mix old and new batteries.**

5. Clean the unit's seal, and the corresponding mating surface, using a damp, non-abrasive cloth.
6. Re-fit the lid, tightening the bolts starting on opposite diagonals.
7. Turn on the unit by pressing and holding the on-off switch until the unit's LED lights green.

Disposal

- Data loggers, accessories and batteries should be disposed of at organised facilities, where available, in line with local regulations.
- In accordance with the WEEE directive Gemini Data Loggers (UK) Ltd. will take back and dispose of any equipment purchased directly. Equipment not purchased directly should be returned to the point of sale for disposal.



Approvals

Gemini Data Loggers (UK) Ltd. operates a Business Management System which conforms to ISO 9001 and ISO 14001.



Further Information

If you should have any questions whilst servicing your data logger, please contact your supplier, or Gemini technical support at:

e: help@tinytag.info t: +44(0)1243 813009